

Naam

Klas

Besturings formule: $A+ \mid A- \mid B+ \mid T1 \mid B- \mid C-$
 $I \mid II \mid III \mid C+ \mid IV$

stop = C- B- A-

Timer1 = 2 sec

Counter = 3 x

A+ = $I \cdot start \cdot stop \cdot (\text{counter})$

A- = $II + stop \cdot c0 \cdot b0$

B+ = $a0 \cdot II \cdot stop$

B- = $t1 \cdot III + stop \cdot c0$

C+ = $t1 \cdot III \cdot stop$

C- = $IV + stop$

M1 = $c0 \cdot start \cdot stop \cdot \overline{I} \cdot \overline{II} \cdot \overline{III} \cdot \overline{IV} + \overline{a1} \cdot I \cdot stop$ ↑ counter

M2 = $a1 \cdot I \cdot stop + \overline{b1} \cdot II \cdot stop$

M3 = $b1 \cdot II \cdot stop + \overline{b0} \cdot III \cdot stop + \overline{c1} \cdot III \cdot stop$

M4 = $b0 \cdot c1 \cdot III \cdot stop + \overline{c0} \cdot IV \cdot stop$

T1 = $III (stop)$

Allocation list

I1 = a0 Q1 = A+

I2 = a1 Q2 = A-

I3 = b0 Q3 = B+

I4 = b1 Q4 = B-

I5 = c0 Q5 = C+

I6 = c1 Q6 = C-

I7 = start

I8 = stop

ig = counter reset.







